



F19

Fingerprint Standalone Access Control

F19 is an innovative biometric fingerprint reader for access control application, offering unparalleled performance by using an advanced algorithm for reliability, precision and excellent matching speed. The F19 features the fastest commercial-based fingerprint matching algorithm and ZK high-performance, high-image quality infrared detection fingerprint sensor. The device offers flexibility to be installed standalone or with any third party access control panels that support standard Wiegand signal. All the operation can be done on the TFT-LCD color screen. The fingerprint image will be displayed on it. That will guide user to put finger on proper position and increase recognition rate. TCP/IP and RS485 are available that the device can be used in different network.

Features



- ▶ **TFT-LCD color screen**
- * Audio-visual indication for acceptance and rejection of valid/invalid fingerprints
- * More simple and convenient operation



- ▶ **Slim and elegant design**
- * Streamlined and slim design for narrow spaces



- ▶ **Fast and accurate fingerprint algorithm**
- * User recognition in 1 second
- * Store 3,000 fingerprint templates and 30,000 transactions



- ▶ **Easy installation and connectivity**
- * Wiegand input & output
- * Network interface by TCP/IP or RS485



- ▶ **Full access control features**
- * Webserver
- * Anti-passback
- * Access control interface for 3rd party electric lock, door sensor, exit button, alarm



- ▶ **Easy operation and management**
- * Work with computer
- * Buzzer, 4x4 keypads and doorbell
- * Built-in serial and Ethernet ports
- * Built-in USB port allows for manual data transfer

Specifications:

Fingerprint Capacity	3000 Templates
Transaction Capacity	30,000 Transactions
Sensor	ZK Optical sensor
Algorithm Version	ZK Finger V9.0&10.0
Communication	RS232/485, TCP/IP, USB-host
Access Control Interface	3rd Party Electric Lock, Door Sensor, Exit Button, Alarm, Door Bell
Wiegand Signal	Input and Output
Display	TFT LCD Color Screen
Interface Styles	Common, Matrix and Magic styles
Standard Function	Webserver, Anti-passback
Optional Function	ID Card, Mifare Card
Power Supply	12V DC,3A
Operating Temperature	0 °C - 45 °C
Operating Humidity	20%-80%
Dimension(W*H*D)	87*195*42.5mm

Optional Accessories:



FR1200

RFID Reader

Exit Button

Electric Lock

Alarm

Door Sensor

Configuration:



Application:



Networked Security:
School



Networked Security:
Building



Standalone Access Control:
Shop



Standalone Access Control:
House



Time Attendance:
Factory



Time Attendance:
Office

ZKTeco Inc.

ZK Mansion, Wuhe Rd, Gangtuo, Bantian, Buji Town, Longgang District, Shenzhen China 518129 Tel: +86-755-8960 2345/46/47/48 Fax: +86-755-8960 2675 www.zkteco.com

Global Service Hotline:
USA: + 1 732-412-6007
EU: +34 916532891
Brazil: +55 11-5082-4315
Thailand: +66-29144238
Mexico: +52-55-52078969
South Africa: +27 12 259 1047
Dubai: +971 4 6091 310
India: +91-0124-2623170
Indonesia: +62 21 2921 8949

